

Datamate J-Tek Connectors

Female Metal Backshell

- ❖ Supplied as an accessory kit, including metal backshell, e-clips and the applicable jackscrews.
- ❖ To be used with the appropriate size of Female Crimp Kit without jackscrews.
- ❖ Gives 360 degree shielding when used with conductive braid and mated to a compatible male connector with metal backshell.
- ❖ Instruction sheets available at www.harwin.com/instructions.



FEMALE		CALCULATION											
		A	$B + 16.2$										
		B	Equivalent no. of contacts - 2										
		C	$B + 7$										
		D	$B + 0.8$										
E-CLIP TOOL		BAND-IT TIE											
<ul style="list-style-type: none"> ❖ For assembling E-Clips supplied with kit. 		<ul style="list-style-type: none"> ❖ For fixing braid to rear collar (requires Tie Dex II A30199 Micro Band tool). 											
<table border="1"> <thead> <tr> <th colspan="2">ORDER CODE</th> </tr> </thead> <tbody> <tr> <td>Z80-300</td> <td></td> </tr> </tbody> </table>		ORDER CODE		Z80-300		<table border="1"> <thead> <tr> <th colspan="2">ORDER CODE</th> </tr> </thead> <tbody> <tr> <td>M80-9470000</td> <td>Length = 206.8mm</td> </tr> <tr> <td>M80-9480000</td> <td>Length = 362.0mm</td> </tr> </tbody> </table>		ORDER CODE		M80-9470000	Length = 206.8mm	M80-9480000	Length = 362.0mm
ORDER CODE													
Z80-300													
ORDER CODE													
M80-9470000	Length = 206.8mm												
M80-9480000	Length = 362.0mm												
HOW TO ORDER													
M80 - 94 X XX 02													
<table border="1"> <thead> <tr> <th colspan="2">SERIES CODE</th> </tr> </thead> <tbody> <tr> <td>M80</td> <td>94</td> </tr> </tbody> </table>		SERIES CODE		M80	94	<table border="1"> <thead> <tr> <th colspan="2">FINISH</th> </tr> </thead> <tbody> <tr> <td>02</td> <td>Nickel</td> </tr> </tbody> </table>		FINISH		02	Nickel		
SERIES CODE													
M80	94												
FINISH													
02	Nickel												
<table border="1"> <thead> <tr> <th colspan="2">TYPE</th> </tr> </thead> <tbody> <tr> <td>5</td> <td>With Slotted Jackscrews</td> </tr> <tr> <td>6</td> <td>With Hex Socket Jackscrews</td> </tr> </tbody> </table>		TYPE		5	With Slotted Jackscrews	6	With Hex Socket Jackscrews	<table border="1"> <thead> <tr> <th colspan="2">EQUIVALENT NO. OF SIGNAL CONTACTS</th> </tr> </thead> <tbody> <tr> <td colspan="2">08, 10, 12, 14, 16, 18, 20, 22, 24, 28, 32</td> </tr> </tbody> </table>		EQUIVALENT NO. OF SIGNAL CONTACTS		08, 10, 12, 14, 16, 18, 20, 22, 24, 28, 32	
TYPE													
5	With Slotted Jackscrews												
6	With Hex Socket Jackscrews												
EQUIVALENT NO. OF SIGNAL CONTACTS													
08, 10, 12, 14, 16, 18, 20, 22, 24, 28, 32													

All dimensions in mm.