

Datamate J-Tek Connectors

DATAMATE J-TEK

Male Vertical Surface Mount

- Gull wing SMT tails simplify inspection process.
- Board Mount provides PCB strain relief.
- Optional pick and place cap.
- Mates with female Datamate J-Tek connectors with compatible jackscrews.



WITHOUT JACKSCREWS		WITH JACKSCREWS		WITH BOARD MOUNT																													
<p>Recommended PC Board Pattern</p>		<table border="1"> <thead> <tr> <th colspan="2">CALCULATION</th> </tr> </thead> <tbody> <tr> <td>A</td> <td>B + 12</td> </tr> <tr> <td>B</td> <td>Total no. of contacts - 2</td> </tr> <tr> <td>C</td> <td>B + 7</td> </tr> </tbody> </table>		CALCULATION		A	B + 12	B	Total no. of contacts - 2	C	B + 7																						
CALCULATION																																	
A	B + 12																																
B	Total no. of contacts - 2																																
C	B + 7																																
HOW TO ORDER																																	
M80 - 5 XX XX XX P																																	
<table border="1"> <thead> <tr> <th colspan="2">SERIES CODE</th> </tr> </thead> <tbody> <tr> <td>02</td> <td>With Jackscrews</td> </tr> <tr> <td>12</td> <td>With 3.5mm Board Mount</td> </tr> <tr> <td>13</td> <td>With 5mm Board Mount</td> </tr> <tr> <td>22</td> <td>Without Jackscrews</td> </tr> </tbody> </table>		SERIES CODE		02	With Jackscrews	12	With 3.5mm Board Mount	13	With 5mm Board Mount	22	Without Jackscrews	<table border="1"> <thead> <tr> <th colspan="2">PICK AND PLACE CAP</th> </tr> </thead> <tbody> <tr> <td>BLANK</td> <td>No Cap</td> </tr> <tr> <td>P</td> <td>Pick & Place Cap</td> </tr> </tbody> </table>		PICK AND PLACE CAP		BLANK	No Cap	P	Pick & Place Cap	<table border="1"> <thead> <tr> <th colspan="2">FINISH</th> </tr> </thead> <tbody> <tr> <td>05</td> <td>Gold</td> </tr> <tr> <td>42</td> <td>Gold + Tin</td> </tr> </tbody> </table>		FINISH		05	Gold	42	Gold + Tin	<table border="1"> <thead> <tr> <th colspan="2">TOTAL NO. OF CONTACTS</th> </tr> </thead> <tbody> <tr> <td colspan="2">04, 06, 08, 10, 12, 14, 20, 26, 34, 42, 50</td> </tr> </tbody> </table>		TOTAL NO. OF CONTACTS		04, 06, 08, 10, 12, 14, 20, 26, 34, 42, 50	
SERIES CODE																																	
02	With Jackscrews																																
12	With 3.5mm Board Mount																																
13	With 5mm Board Mount																																
22	Without Jackscrews																																
PICK AND PLACE CAP																																	
BLANK	No Cap																																
P	Pick & Place Cap																																
FINISH																																	
05	Gold																																
42	Gold + Tin																																
TOTAL NO. OF CONTACTS																																	
04, 06, 08, 10, 12, 14, 20, 26, 34, 42, 50																																	

All dimensions in mm.