

# Datamate L-Tek Connectors

DATAMATE L-TEK

## Female Crimp Kit

- Part numbers are for a complete kit of a housing and the applicable number of contacts.
- Contacts are rear insertable.
- Spare contacts are available – see the following page.



SINGLE ROW	CALCULATION	DOUBLE ROW	CALCULATION
	<b>A</b> B + 5.15		<b>A</b> B + 5.15
	<b>B</b> (Total no. of contacts - 1) x 2		<b>B</b> Total no. of contacts - 2

TOOLS	WIRE STRIPPING DETAILS
<p><b>Recommended Crimp Tool</b> - M22520/2-01</p> <p><b>Positioner</b> - T5747</p> <p><b>Contact Insertion/Removal Tool</b> - Z80-280</p> <ul style="list-style-type: none"> <li>Spare and pre-cabled contacts shown on following pages.</li> <li>Instruction sheets available at <a href="http://www.harwin.com/instructions">www.harwin.com/instructions</a>.</li> </ul>	

## HOW TO ORDER

**M80 - XXX XX XX**

<b>SERIES CODE</b>		<b>FINISH</b>																								
<table border="1" style="width: 100%;"> <thead> <tr> <th colspan="2" style="background-color: #f4a460;">TYPE</th> </tr> </thead> <tbody> <tr> <td style="background-color: #f4a460;"><b>798</b></td> <td>Single Row, Extra Small Bore (28-32 AWG)</td> </tr> <tr> <td style="background-color: #f4a460;"><b>898</b></td> <td>Single Row, Small Bore (24-28 AWG)</td> </tr> <tr> <td style="background-color: #f4a460;"><b>899</b></td> <td>Single Row, Large Bore (22 AWG)</td> </tr> <tr> <td style="background-color: #f4a460;"><b>788</b></td> <td>Double Row, Extra Small Bore (28-32 AWG)</td> </tr> <tr> <td style="background-color: #f4a460;"><b>888</b></td> <td>Double Row, Small Bore (24-28 AWG)</td> </tr> <tr> <td style="background-color: #f4a460;"><b>889</b></td> <td>Double Row, Large Bore (22 AWG)</td> </tr> </tbody> </table>	TYPE		<b>798</b>	Single Row, Extra Small Bore (28-32 AWG)	<b>898</b>	Single Row, Small Bore (24-28 AWG)	<b>899</b>	Single Row, Large Bore (22 AWG)	<b>788</b>	Double Row, Extra Small Bore (28-32 AWG)	<b>888</b>	Double Row, Small Bore (24-28 AWG)	<b>889</b>	Double Row, Large Bore (22 AWG)	<table border="1" style="width: 100%;"> <thead> <tr> <th colspan="2" style="background-color: #f4a460;">TOTAL NO. OF CONTACTS</th> </tr> </thead> <tbody> <tr> <td style="background-color: #f4a460;"><b>02 to 07, 17</b></td> <td>Single Row</td> </tr> <tr> <td style="background-color: #f4a460;"><b>04, 06, 08, 10, 12, 14, 16, 18, 20, 26, 34</b></td> <td>Double Row</td> </tr> </tbody> </table>	TOTAL NO. OF CONTACTS		<b>02 to 07, 17</b>	Single Row	<b>04, 06, 08, 10, 12, 14, 16, 18, 20, 26, 34</b>	Double Row	<table border="1" style="width: 100%;"> <tbody> <tr> <td style="background-color: #f4a460;"><b>01</b></td> <td>Gold + Tin</td> </tr> <tr> <td style="background-color: #f4a460;"><b>05</b></td> <td>Gold</td> </tr> </tbody> </table>	<b>01</b>	Gold + Tin	<b>05</b>	Gold
TYPE																										
<b>798</b>	Single Row, Extra Small Bore (28-32 AWG)																									
<b>898</b>	Single Row, Small Bore (24-28 AWG)																									
<b>899</b>	Single Row, Large Bore (22 AWG)																									
<b>788</b>	Double Row, Extra Small Bore (28-32 AWG)																									
<b>888</b>	Double Row, Small Bore (24-28 AWG)																									
<b>889</b>	Double Row, Large Bore (22 AWG)																									
TOTAL NO. OF CONTACTS																										
<b>02 to 07, 17</b>	Single Row																									
<b>04, 06, 08, 10, 12, 14, 16, 18, 20, 26, 34</b>	Double Row																									
<b>01</b>	Gold + Tin																									
<b>05</b>	Gold																									

All dimensions in mm.